



梁

可動範圍

The drawing consists of two views of a mechanical part. The top view is a rectangle with a smaller rectangle inside it, representing a hole. The bottom view is a circle, representing the end of the cylinder. A horizontal centerline passes through the center of both the rectangle and the circle. The hole is positioned such that its center is on the centerline, and its width is less than the diameter of the cylinder.

回轉角度
360°

- 【照射物近接限度10cm】



✖

本図面は2枚1組です。 1 / 2

6	LEDフラットランプ		単色 拡散タイプ
5	ソケット		□金GX53-1
4	アーム	アルミダイカスト	ホワイトつや消し ポリエステル粉体塗装
3	取付板	亜鉛鋼板 (t1.2)	
2	フランジ	PBT樹脂	ホワイト
1	セード	PBT樹脂	ホワイト
部 番	部 品 名	材 質 ・ 素 材 厚	備 考

関

今
岡

部 番	部 品 名	材 質 ・ 素 材 厚	備 考	パナソニック株式会社
-----	-------	-------------	-----	------------



<施工上のご注意>

- ほたるスイッチと接続する場合は1回路につきスイッチ3個まででご使用ください。
(4個以上のほたるスイッチと接続すると、スイッチを切にしても器具が消灯しないことがあります。)
- かつてにスイッチなどの高機能スイッチを使用する場合は、起動方式CE1に適合した当社製スイッチを使用し、
接続台数、接続方法はスイッチの取扱説明書に従ってください。
- 当社製壁スイッチ品番WT5001、WT5002、WT50519、WT50529を
ご使用の場合は、スイッチ1個につき16台まで使用可能です。
上記以外のスイッチは8台まででご使用可能です。

<使用上のご注意>

- 器具には、適合LEDフラットランプ（パナソニック製推奨）をご使用ください。
- LEDにはバラツキがあるため、同一品番商品でも商品ごとに発光色、明るさが異なる場合があります。
- 器具の近くでは、ラジオやテレビなどの音響、映像機器に雑音が入る場合があります。
- 器具の近くでは、電子錠などに使用する光高周波方式のリモコンが動作しない場合が
ごくまれにありますので、ご注意ください。
- 高機能スイッチの適合および接続台数は、以下のWebサイトよりご確認ください。
■高機能スイッチのLED照明器具接続台数表
https://www2.panasonic.biz/jp/densetsu/haisen/switch_concent/pdf/daisu.pdf

本図面は2枚1組です。 2/2

特記事項	5				品名 スポットライト XAS3002NCE1
	4				
	3				
	2				今岡 川端
	1				
	部番	部 品 名	材質・素材厚	備 考	パナソニック株式会社

