



-
- 取付ボルト設置図

Technical drawings of the LED lighting fixture showing front, side, and detail views with dimensions and labels.

Front View Dimensions:

- Width: 237 ± 4
- Height: 380 ± 4
- Internal width: 244 ± 4
- Internal height: 190 ± 4

Side View Dimensions:


- Top width: 117
- Mounting arm height: 120
- Base height: 161

Labels and Callouts:

- 1: 首振り固定ネジ (Swivel fixed screw)
- 2: M8六角ボルト (M8 hex bolt)
- 3: 落下防止ワイヤー (Fall prevention wire)
- 4: 位置決めナット2個 (別送) (Positioning nut 2 pieces (separate))
- 5: 本体 (Main body)
- 6, 7: 照明器具取付面 (Light fixture mounting surface)
- 8: 座金・ダブルナット (別送) (Washer/double nut (separate))
- 9: M10ボルト (M10 bolt)

Other Labels:

- (ステンレス製 $\phi 3$) (Stainless steel $\phi 3$)
- M4回止めネジ (取付架台用) $\phi 18$ 穴 (M4 stop screw (mounting bracket use) $\phi 18$ hole)
- 2-15X18長穴 (直付け・アーム取付用) (2-15X18 long hole (direct mount/arm mount use))
- 落下防止取付金具 (Fall prevention mounting bracket)
- $\phi 11$ 穴 (Fall prevention mounting bracket)
- 位置決めナット2個 (別送) (Positioning nut 2 pieces (separate))
- 座金・ダブルナット (別送) で M10ボルト 取付けてください。 (Use washer/double nut (separate) to attach M10 bolt.)
- ワイヤー取付位置は、照明器具取付面と同じ面になるように取付けてください。 (The wire mounting position should be attached to the same surface as the light fixture mounting surface.)
- 落下防止取付金具部 (Fall prevention mounting bracket part)



定格

定格電圧	AC100V	AC200V	AC242V
入力電流	0.49A	0.25A	0.21A
消費電力	48.7W	49.5W	48.9W
周波数	50Hz/60Hz共用		

C 0 5

單位：mm 第三角法 (JIS A-4)

NNY24900-K8

