

屋内照明器具特性

| | | |
|---------|----------------|-----------|
| 品番 (品名) | XSZR1071V | |
| 光源 | LLD2411VCB1 ×1 | 500.0 l m |
| 管理番号 | K0192058(0)DB1 | |
| BZ分類 | BZ1 | |

| | | | | | | | | | | | | | | | | | | | | | |
|--------|---------------|-----------------|------|--------|---------|--------|------|------|------|------|------|------|------|------|------|------|------|------|------|------|------|
| 器具効率 | 88% | 天井 | 80% | | | | 70% | | | | 50% | | | | 30% | | | | 0% | | |
| | 上方光束 | | 0% | 70 | 50 | 30 | 10 | 70 | 50 | 30 | 10 | 70 | 50 | 30 | 10 | 70 | 50 | 30 | 10 | 0% | |
| 下方光束 | 88% | 床 | 10% | | | | 10% | | | | 10% | | | | 10% | | | | 0% | | |
| 室指数 | 照明率 (X0.01) | | | | | | | | | | | | | | | | | | | | ZCM |
| 保守率 | 良 | 0.63 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | |
| | 中 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | 0.6 | |
| | 否 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | 0.56 | |
| 下方投影面積 | 等価発光面積 | cm ² | 1.25 | 1.5 | 2.0 | 2.5 | 3.0 | 4.0 | 5.0 | 7.0 | 10.0 | 0.6 | 0.8 | 1.0 | 1.25 | 1.5 | 2.0 | 2.5 | 3.0 | 4.0 | |
| | | | 83 | 85 | 87 | 89 | 90 | 91 | 92 | 92 | 93 | 94 | 69 | 75 | 79 | 83 | 85 | 87 | 89 | 90 | 92 |
| 取付高さ | 器具間隔最大限 | | Hm | 0.74Hm | 縦方向 (B) | 0.74Hm | 3.0 | 4.0 | 5.0 | 7.0 | 10.0 | 62 | 66 | 69 | 71 | 73 | 74 | 75 | 76 | 77 | 78 |
| | 横方向 (A) | 62 | | | | | 66 | 69 | 71 | 73 | 74 | 75 | 76 | 77 | 78 | 79 | 80 | 81 | 82 | 82 | 83 |
| | | | | | | 4.0 | 5.0 | 7.0 | 10.0 | 0.6 | 0.8 | 1.0 | 1.25 | 1.5 | 2.0 | 2.5 | 3.0 | 4.0 | 5.0 | 7.0 | 10.0 |
| | | | | | | 4.0 | 5.0 | 7.0 | 10.0 | 0.6 | 0.8 | 1.0 | 1.25 | 1.5 | 2.0 | 2.5 | 3.0 | 4.0 | 5.0 | 7.0 | 10.0 |
| | | | | | | 4.0 | 5.0 | 7.0 | 10.0 | 0.6 | 0.8 | 1.0 | 1.25 | 1.5 | 2.0 | 2.5 | 3.0 | 4.0 | 5.0 | 7.0 | 10.0 |
| | | | | | | 4.0 | 5.0 | 7.0 | 10.0 | 0.6 | 0.8 | 1.0 | 1.25 | 1.5 | 2.0 | 2.5 | 3.0 | 4.0 | 5.0 | 7.0 | 10.0 |

